

THE NEXT GENERATION OF ELECTRONIC BALLASTS... IS HERE

NEXT GEN™ ELECTRONIC BALLAST

600w/400w
90v-260v



FEATURES

- Runs Either 400w or 600w Bulbs
- 90v-260v Input Voltage
- Runs Either M.H. or H.P.S. Bulbs
- 30% more Light than a Core and Coil Ballast
- Fast Lamp Ignition
Cold Lamp Starts in Less than 2 Seconds
Hot Lamp Restart in Less than 2 Minutes
- Universal Lamp Receptacle
- Bulb can be ran up to 65' from Ballast
- Flicker-Free Operation
- Constant Lamp Voltage Prolongs Bulb Life

SPECIFICATIONS

400w: 3.5 amps at 120v	Dimensions: 9.5" x 7" x 2"
400w: 1.75 amps at 240v	Weight: 4.25 lbs
600w: 5.7 amps at 120v	Operating Temp: 0-140°F
600w: 2.8 amps at 240v	Cold Lamp Start: < 2 sec.
Power Factor: 99.99	Hot Lamp Start: < 2 min.
Max Lamp Cord Length: 65'	

INSTRUCTIONS

1. Hang your reflector in the appropriate location and screw your lamp into the reflector socket.
2. Switch the selector to match the lamp wattage.



3. Attach the power cord to the power receptacle on the ballast.
4. Plug in the reflector lamp cord into the appropriate receptacle on the ballast. You cannot run 2 bulbs at the same time.
5. Plug power cord into your power source (wall outlet or Lighting Controller).

1. C.A.P. & Common
2. HF
3. PL
4. Foreign



WARRANTY

5 Year Warranty*

*Certain conditions apply

C.A.P. warrants the NextGen Digital Ballast to be free from defects in materials or workmanship for a period of 5 years. 3 Year full warranty and 2 year pro-rated warranty. Misuse, abuse, or failure to follow instructions are not covered. C.A.P. will, at our discretion, repair or replace the product covered under this limited warranty that are returned to our facility. To request warranty service, you must take the product to the place of purchase. If warranty service is required, C.A.P. will issue a RMA number. The product must be shipped back to C.A.P. in the original or equivalent packaging, prepaid shipping charges, and insured. We can not cover shipping damages. Pack your product well.



CUSTOM AUTOMATED PRODUCTS
4745 Hiers Ave., Suite A, Riverside, CA 92505
www.capcontrollers.com • 866-476-9768